



18 IN.

ACCESS® LED LIGHT INSTALLATION INSTRUCTIONS

NOTE: Requires (3) AA batteries, not included in kit.

A. Open battery box with Phillips head screwdriver and install (3) AA batteries.

TIP: Change auto shutoff time while battery box is open.

B. Reattach box cover, do not overtighten screws.

NOTE: For best adhesion, air and surface temperature should be above 60 °F for at least 2 hours before adhering the LED light.

C. Clean area where LED light will be attached with soap and water or rubbing alcohol, wipe dry.

D. Peel protective layer from adhesive strip and battery box to adhere.

E. Firmly press battery box and LED light strip to secure in place.



WARNING:

Cancer and Reproductive Harm
www.P65Warnings.ca.gov

CE FC

MADE IN CHINA

90392_B

CHANGING AUTO SHUTOFF TIME

ACCESS® Motion LED Light automatically turns on when motion sensor detects movement and will stay on for selected amount of time after sensor stops detecting movement.

AUTO SHUTOFF SWITCH SETTINGS:

- Slide to left for 1 minute (factory default)
- Slide to middle for 3 minutes
- Slide to right for 5 minutes

NOTE: If not dark enough to activate motion sensor, simply cover light sensor to activate LED light.

ACCESSLEDLIGHT.COM

Reorder #90392

